



The Huck® Range Force™ Battery Tool

A Portable Powerhouse For Multiple Applications and Industries

Howmet Fastening Systems and Makita® bring you industry-leading performance with the latest advancement in battery-powered and adjustable force installation tooling. The new Huck® Range Force™ battery tool* has an electronically adjustable pull force and long stroke to enable installation of structural and non-structural rivets and up to 1/4″ two-piece HuckBolt® fasteners.** Along with an 18V 5Ah battery, the Huck Range Force by Makita is a force to be reckoned with in portability, reliability and versatility.







Transportation



Construction

Features and Benefits

- Electronically Adjustable Pull Force Control
- Designed for Huck Installation Nose Assemblies

Capacity: 3/16" (4.8 mm) – 1/4" (6.4 mm)

Stroke Length: 1.18" (30 mm)

Pulling Force: BV4500-118 up to 4500 lbf (20kN)

BV2200-118 up to 2200 lbf (10kN)

Weight: 4.8 lbs with 1.5 Ah Battery - 5.5 lbs with 5 Ah Battery

Battery Pack: 18V / Li-ion / 5 Ah

Recharge Time: Approximately 45 minutes

- Cross-Compatibility with Other Makita 18v Batteries
- \bullet High Pull Force and Long Stroke Enable Installation of Both Structural and Non-Structural Rivets, and up to 1/4" Two-Piece HuckBolt Fasteners**

Tool Packages & Accessories	
PART NO.	DESCRIPTION
BV2200-118K0	2200 lbf Battery Tool and Carrying Case
BV2200-118K2	2200 lbf Battery Tool, Two Batteries, One Charger, Carrying Case
BV4500-118K0	4500 LBF BATTERY TOOL AND CARRYING CASE
BV4500-118K2	4500 lbf Battery Tool, Two Batteries, One Charger and Carrying Case
MB-1850	BV Extra Battery - 18V, 5Ah
MCH-18-120	BV BATTERY CHARGER
BV4500RETROKIT	131646 - RUBBER PINTAIL BOTTLE
	131645 - Bottle Adapter

 $[\]ensuremath{^{*}}$ The Huck Range Force is a Lockbolt / Blind Rivet Installation Tool.



^{**} Excludes 1/4" BOM.